

TMSS10LibraryManager

TMSS10LibraryManager will synchronize one TapeTrack Server with another.

Synopsis

```
TMSS10LibraryManager [-C Customer-ID] [-M Media-ID] [-R Repository-ID] [-S  
logon string] [-T target repository] [-V volume filter] [-c configuration  
file] [-e ejection filter] [-f minimum free slots] [-s minimum scratch  
volumes]
```

Options

- -C [Customer-ID](#)
- -M [Media-ID](#)
- -R [Repository-ID](#)
- -S The Logon string argument sets the [Server Logon Information](#)
- -T Target [Repository](#) for Volumes if ejection is required to make room for minimum Scratch quantity. If not specified, no Volumes will be ejected.
- -V [Volume Filter](#) which can be used to filter the traversal of [Customer](#), [Media](#), [Volume](#), [Repository](#) and [Flag](#) values.
- -c The config file argument specifies the path to the Batch Configuration File. The Batch Configuration File allows you to perform advanced traversal of [Customer](#), [Media](#) and [Volumes](#), perform advanced Barcode pre and post processing and route program output to syslogd. Configuration File capabilities vary from program to program but the syntax remains the same. In the event that logic is not supported it will simply be ignored.
- -e [Volume](#) ejection exclusion filter
- -f Minimum free Slots required in [Repository](#) ([Repository](#) Properties override)
- -s Minimum Scratch [Volumes](#) required in [Repository](#) ([Repository](#) Properties override)

Technical Support

The TapeTrack Software is commercially supported by a full time help desk staff.

If you are experiencing problems or want some advice on how to configure or use the product please see the [Accessing Technical Support](#) page.

Exit Statuses

1. **zero** Program has ended successfully.
2. **non-zero** Program has not ended successfully.

Environment

Files

stdout: Output Reports.

stderr: Diagnostic messages.

stdin: Program input.

Example

Command line syntax

```
<sxh plain;> TMSS10LibraryManager -S user:-password@server -C US02 -M LTO -R LIBR </sxh>
```

Output

The output of the TapeTrack Library Manager program is described in detail on the page [Library Management Report](#)

Changelog

Cannot load rss feed.

From:
<https://docs.tapetrack.com/> - **TapeTrack Documentation**

Permanent link:
<https://docs.tapetrack.com/cli/tmss10librarymanager?rev=1584931881>

Last update: **2025/01/21 22:07**

