TMSS10ZoneList

TMSS10ZoneList lists each Zone and the Volumes assigned to them.

Synopsis

```
TMSS10ZoneList [-S logon string] [-V volume filter] [-f report format]
```

Options

- `-S` The Logon string argument sets the Server Logon Information
- `-V` Volume Filter which can be used to filter the traversal of Customer, Media, Volume, Repository and Flag values.
- `-f` Report format.

If an argument value starts with the value `FI:`, the value for that attribute will be read from the file name specified immediately after it. For example, if a file named ACME_volumes has the content `ACME_*.*`, specifying `FI:/etc/ACME_volumes` will have the same effect as `-V ACME.*.*`. Using `FI:` to refer to a file for an attribute value works for all attributes.

If the pattern being matched starts with *LIST: then rather than matching the literal value, each record in the file specified as *LIST:filename will be tested. If one matches the match will succeed.

2025/01/21 22:08
include page

Technical Support

The TapeTrack Software is commercially supported by a full time help desk staff.

If you are experiencing problems or want some advice on how to configure or use the product please see the Accessing Technical Support page.

Exit Statuses

1. **zero** Program has ended successfully.
2. **non-zero** Program has not ended successfully.

Environment

Files

stdout: Output Reports.
stderr: Diagnostic messages.
stdin: Program input.

Example

Zone List Report - format 1

Command line syntax

<sxh plain;> TMSS10ZoneList -S user:-password@server -f 1 </sxh>

Output

<sxh plain;>

System: TapeTrack Report Description: Zone Inventory

```
     Report Notes: ZoneID(1:1) Description(Drawer 1 divider 1)
     Report Width: 113 bytes
```

Seq. Customer Media Type Barcode Slot Next Move —— ——————————————- ————————– ————————– ————- ————-

```
    1 North Carolina Data Center              LTO Cartridge
US03.LTO.000000L5           1.1
    2 North Carolina Data Center              LTO Cartridge
US03.LTO.000001L5           1.2
    3 North Carolina Data Center              LTO Cartridge
US03.LTO.000002L5           1.3
    4 North Carolina Data Center              LTO Cartridge
US03.LTO.000003L5           1.4
    5 North Carolina Data Center              LTO Cartridge
US03.LTO.000004L5           1.5
    6 North Carolina Data Center              LTO Cartridge
US03.LTO.000005L5           1.6
    7 North Carolina Data Center              LTO Cartridge
US03.LTO.000006L5           1.7
    8 North Carolina Data Center              LTO Cartridge
US03.LTO.000007L5           1.8
```

—— ——————————————- ————————– ————————– ————- ————-

```
            System: TapeTrack
```

Report Description: Zone Inventory

```
     Report Notes: ZoneID(GEMTRAC1) Description(GemTrac Rack 1)
     Report Width: 113 bytes
```

Seq. Customer Media Type Barcode Slot Next Move —— ——————————————- ———————– ——————– ———- ———-

```
    1 Los Angeles Data Center                  LTO Cartridge
US02.LTO.000001L6           1.1
    2 Los Angeles Data Center                  LTO Cartridge
US02.LTO.000005L6          1.16 1970-01-05
    3 Los Angeles Data Center                  LTO Cartridge
US02.LTO.000024L6          1.19
    4 Los Angeles Data Center                  LTO Cartridge
US02.LTO.000025L6          1.20
    5 Los Angeles Data Center                  LTO Cartridge
US02.LTO.000027L6          1.21
    6 Los Angeles Data Center                  LTO Cartridge
US02.LTO.000028L6          1.22
    7 Los Angeles Data Center                  LTO Cartridge
US02.LTO.000029L6          1.23
    8 Los Angeles Data Center                  LTO Cartridge
US02.LTO.000030L6          1.24
    9 Los Angeles Data Center                  LTO Cartridge
US02.LTO.000031L6          1.25
   10 Los Angeles Data Center                  LTO Cartridge
US02.LTO.000032L6          1.26
   11 Los Angeles Data Center                  LTO Cartridge
US02.LTO.000033L6          1.27
   12 Los Angeles Data Center                  LTO Cartridge
US02.LTO.000034L6          1.28
```

—— ——————————————- ——————– ——————– ———- ———- </sxh>

Zone List Report - format 2 (default)

Command line syntax

<sxh plain;> TMSS10ZoneList -S user:-password@server -f 2 </sxh>

Output

<sxh plain;>

```
           System: TapeTrack
```

Report Description: Zone Allocation

```
     Report Width: 112 bytes
```

Seq. Customer Media Type Repository Zone —— ————————————————- ————————– ————————– ————————– 1 Los Angeles Data Center LTO Cartridge Offsite Vault GEMTRAC1

```
    2 -                                          -                    -
GEMTRAC2
    3 North Carolina Data Center                 LTO Cartridge        Offsite
Vault        GEMTRAC4
```

—— ————————————————- ————————– ————————– ————————–

</sxh>

Changelog

Cannot load rss feed.

From:
https://docs.tapetrack.com/ - **TapeTrack Documentation**

Permanent link:
https://docs.tapetrack.com/cli/tmss10zonelist?rev=1623815380

Last update: **2025/01/21 22:07**