

TMSS10ZoneList

TMSS10ZoneList lists each [Zone](#) and the [Volumes](#) assigned to them.

Synopsis

```
TMSS10ZoneList [-S logon string] [-V volume filter] [-f report format]
```

Options

- -S The Logon string argument sets the [Server Logon Information](#)
- -V [Volume Filter](#) which can be used to filter the traversal of [Customer](#), [Media](#), [Volume](#), [Repository](#) and [Flag](#) values.
- -f Report format.

If an argument value starts with the value FI:, the value for that attribute will be read from the file name specified immediately after it. For example, if a file named ACME_volumes has the content ACME_*.*, specifying FI:/etc/ACME_volumes will have the same effect as -V ACME.*.*. Using FI: to refer to a file for an attribute value works for all attributes.

If the pattern being matched starts with *LIST: then rather than matching the literal value, each record in the file specified as *LIST:filename will be tested. If one matches the match will succeed.

2025/01/21 22:08

[include page](#)

Technical Support

The TapeTrack Software is commercially supported by a full time help desk staff.

If you are experiencing problems or want some advice on how to configure or use the product please see the [Accessing Technical Support](#) page.

Exit Statuses

1. **zero** Program has ended successfully.
2. **non-zero** Program has not ended successfully.

Environment

Files

stdout: Output Reports.
stderr: Diagnostic messages.
stdin: Program input.

Example

Zone List Report - format 1

Command line syntax

```
TMSS10ZoneList -S user:-password@server -f 1
```

Output

System: TapeTrack				
Report Description: Zone Inventory				
Report Notes: ZoneID(1:1) Description(Drawer 1 divider 1)				
Report Width: 113 bytes				
Seq.	Customer	Slot	Next Move	Media Type
Barcode				

1	North Carolina Data Center			LT0 Cartridge
US03.LT0.000000L5		1.1		
2	North Carolina Data Center			LT0 Cartridge
US03.LT0.000001L5		1.2		
3	North Carolina Data Center			LT0 Cartridge
US03.LT0.000002L5		1.3		
4	North Carolina Data Center			LT0 Cartridge
US03.LT0.000003L5		1.4		
5	North Carolina Data Center			LT0 Cartridge
US03.LT0.000004L5		1.5		
6	North Carolina Data Center			LT0 Cartridge
US03.LT0.000005L5		1.6		
7	North Carolina Data Center			LT0 Cartridge
US03.LT0.000006L5		1.7		
8	North Carolina Data Center			LT0 Cartridge
US03.LT0.000007L5		1.8		

System: TapeTrack				
Report Description: Zone Inventory				
Report Notes: ZoneID(GEMTRAC1) Description(GemTrac Rack 1)				

Report Width: 113 bytes

Seq. Barcode	Customer	Slot	Next Move	Media Type

1	Los Angeles Data Center			LT0 Cartridge
US02.LT0.000001L6		1.1		
2	Los Angeles Data Center			LT0 Cartridge
US02.LT0.000005L6		1.16	1970-01-05	
3	Los Angeles Data Center			LT0 Cartridge
US02.LT0.000024L6		1.19		
4	Los Angeles Data Center			LT0 Cartridge
US02.LT0.000025L6		1.20		
5	Los Angeles Data Center			LT0 Cartridge
US02.LT0.000027L6		1.21		
6	Los Angeles Data Center			LT0 Cartridge
US02.LT0.000028L6		1.22		
7	Los Angeles Data Center			LT0 Cartridge
US02.LT0.000029L6		1.23		
8	Los Angeles Data Center			LT0 Cartridge
US02.LT0.000030L6		1.24		
9	Los Angeles Data Center			LT0 Cartridge
US02.LT0.000031L6		1.25		
10	Los Angeles Data Center			LT0 Cartridge
US02.LT0.000032L6		1.26		
11	Los Angeles Data Center			LT0 Cartridge
US02.LT0.000033L6		1.27		
12	Los Angeles Data Center			LT0 Cartridge
US02.LT0.000034L6		1.28		

Zone List Report - format 2 (default)

Command line syntax

```
<sxh plain;> TMSS10ZoneList -S user:-password@server -f 2 </sxh>
```

Output

```
<sxh plain;>
```

System: TapeTrack

Report Description: Zone Allocation

Report Width: 112 bytes

Seq. Customer Media Type Repository Zone — —————

————— 1 Los Angeles Data Center LTO Cartridge Offsite Vault GEMTRAC1

2 -	-	-
GEMTRAC2		
3 North Carolina Data Center	LTO Cartridge	Offsite
Vault GEMTRAC4		

</sxh>

Changelog

Cannot load rss feed.

From:

<https://docs.tapetrack.com/> - TapeTrack Documentation

Permanent link:

<https://docs.tapetrack.com/cli/tmss10zonelist?rev=1626910773>

Last update:

2025/01/21 22:07

